

Speakerphones for individual, small, medium or large group use. The CHAT 150 and CHATAttach 150 USB connect to PCs for rich, full-duplex audio communications and can be used with VoIP softphones, Web collaboration, instant messaging and any other applications requiring two-way audio. A perfect addition to the office or conference room for greatly enhanced collaboration.



### Applications



#### Web Conferencing

IBM Workplace  
Microsoft Live Meeting, WebEx

#### VoIP Softphones

Avaya, Cisco, Nortel, Mirial

#### Internet Telephony

Google Talk, Skype, Vonage

#### Instant Messenger

AOL, Microsoft MSN, Yahoo

### Features



#### Enable full-duplex speakerphone capabilities on PCs or laptops

- + Connect the CHAT 150 or the CHATAttach 150 to laptops & PCs via USB for hands-free audio for:
  - > VoIP softphones
  - > Instant Messaging audio chats
  - > Web conferences

#### Enjoy rich audio playback

- + Full bandwidth frequency response provides rich audio playback with media players

#### Enjoy crisp, clear audio

- + Advanced ClearOne HDConference® audio processing technologies deliver remarkably rich, full audio for natural, effortless conversations:
  - > True full duplex performance allows user to listen and speak at the same time without audio cutting in and out
  - > Distributed Echo Cancellation®
  - > Noise cancellation
  - > Advanced automatic level management

- + Three built-in microphones provide full 360-degree coverage up to 8 feet from device

- + Bridge audio from PC applications with audio on telephone for instant 3-way conference bridge

> CHAT 150 COMPONENTS

> CHATAAttach 150 COMPONENTS



CHAT 150



USB 2.0  
Connection Cable  
Part# 830-156-200



Quick Start Guide  
Part# 800-156-202



Two CHAT 150 Units  
Part# 910-156-200



USB 2.0  
Connection Cable  
Part# 830-156-200



CHATAttach  
Cable  
Part# 830-156-010L




CHATAttach  
Power Supply  
Part# 551-156-200




CHATAttach  
Quick Start Guide  
Part# 800-156-225

> ROOM APPLICATIONS

CHAT 150



CHATAAttach 150



## Functional Specifications

### SYSTEM REQUIREMENTS

Microsoft Windows 7,8,10  
For any firmware upgrades, use Win7  
Mac OS

### CONNECTIONS

**USB:**  
Version 2.0 Compatible  
Type: Mini-B Female

### KEYED CONNECTOR:

Keyed RJ-45 (8-conductor)

### LINE INPUT/OUTPUT VIA VC BREAKOUT BOX (BOB)

#### FREQUENCY RESPONSE:

20 Hz - 20 kHz +/- 1 dB  
Maximum Level: +6 dBu  
Input Impedance: 10 kΩ  
Output Impedance: 50 Ω

### CONTROLS

Volume Up  
Volume Down  
Microphone Mute

### AUDIO

#### SPEAKER:

Bandwidth: 190 Hz - 20 kHz  
Max Output Level:  
85 dB SPL @ 1 foot (0.30 meter)

#### MICROPHONE

Bandwidth: 50 Hz - 7.75 kHz

### ENVIRONMENTAL

#### OPERATING TEMPERATURE:

41 - 104° F (5 - 40° C)

### PROCESSING

Full Duplex  
Distributed Echo Cancellation (D.E.C.)®  
Noise Cancellation (NC)  
Automatic Level Control (ALC)  
Line Echo Cancellation (LEC) - Selectable  
First Mic Priority

### POWER

**USB:**  
5 VDC @ 500 mA Maximum

### EXTERNAL:

Input: 100 - 240 VAC  
Output: 9 VDC @ 560 mA  
Tip: Power  
Ring: Ground

### MECHANICAL

**DIMENSIONS (W X D X H):**  
7.4" x 7.4" x 1.8" (18.8 cm x 18.8 cm x 4.6 cm)  
**WEIGHT:**  
1.17 lbs (0.53 kg)

### COMPLIANCE

RoHS  
REACH  
FCC Class A Part 15  
ICES-003  
CE Listed  
UL Listed

### MODEL NUMBERS

- 910-156-200 CHAT 150 USB  
+ Single CHAT 150 and Connecting Cable
- 910-156-200-00 CHATAAttach 150  
+ Two (2) CHAT 150 Devices, Connecting Cables and Power Supply
- 910-156-222 CHAT 150 Avaya  
+ CHAT 150 and Connecting Cable to Avaya Enterprise Phone
- 910-156-220 CHAT 150 Cisco  
+ CHAT 150 and Connecting Cable to Cisco Enterprise Phone
- 910-156-230 CHAT 150 VC  
+ CHAT 150 and Cable to Video Conference System

### ACCESSORY PART NUMBERS

- 860-156-230L - CHAT 150 VC Accessory Kit  
+ Includes Video Conferencing Breakout Box, Power Adapter, International Power Clips, RCA Connection Cable, 25' Link Cable
- 860-156-222L - CHAT 150 Avaya Accessory Kit  
+ Includes Breakout Box for 2410, 2420, 4610 and 4621 Telephone Handsets, Power Adapter, International Power Clips, RJ-9/RJ-9 Telephone Cable, 25' Link Cable
- 860-156-220L - CHAT 150 Cisco Accessory Kit  
+ Includes Breakout Box for 7940, 7960, and 7970 Telephones, Power Adapter, International Power Clips, RJ-9/RJ-9 Telephone Cable, 25' Link Cable
- 910-156-225 - CHATAAttach Expansion Kit  
+ Includes Cables, Power Supply and Quick Start Guide to Update Two (2) CHAT 150 Devices to CHATAAttach

## ClearOne Contacts

**North America**  
Tel: 801-975-7200  
Toll Free: 800-945-7730  
Sales: 800-707-6994  
Fax: 801-303-5711  
sales@clearone.com

**Europe & Oceania**  
Tel: +44 (0) 1189 036 053  
global@clearone.com

**Asia Pacific**  
Tel: +852 3590 4526  
global@clearone.com

**Latin America**  
Tel: 801-974-3621  
global@clearone.com

**Middle East**  
Tel: +852 3590 4526  
global@clearone.com